

SMART

ELECTRONIC HOOTER (MODEL EH)

SMART ELECTRONIC HOOTER is a solid-State Electronic Hooter of 30 Watt with a siren Tone of 40 sec with Sound output is 107 dB@ 1 meter @ 30W. An Internal Volume control Pot is provided for output volume control, 2 external loud speaker horns of 8 ohms 60 Watt are connected with the unit. The MAIN CONTROL CARD with power transformer is fitted in a wall mountable type IP 55/65 grade ABS body housing of Grey colour, weighing about 850gms with **military grade** connectors for speaker output & power input, Works on 220/110 V AC.



VERSATILE APPLICATIONS: -

- * Cement Plants. * Mines. * Petrochemical Refineries. * Steel Plants. * Spinning Yarns * Fertilizer Plants. * Sugar Mills. * Power Generation Facilities * Pulp & Paper Mills * Recreation Facilities * Hydroelectric Facilities * Drilling Rigs * Process industries * ANY LARGE AND MEDIUM SCALE INDUSTRIAL UNITS.

SMART FEATURES: -

- Operating on 220/110 V AC (PREDEFINED)
- Siren Tone for 40 sec @ 30 Watt
- Sound output is 107 dB @ 1 meter @ 30W.
- Internal Volume control Pot & 2 external loud speaker horns of 8 ohms 60
- ABS body with IP 55/65 grade
- Military grade connectors for speaker output & power input.

TECHNICAL SPECIFICATIONS: -

ELECTRICAL :-

Tone frequency range	300Hz to 1000Hz
Power Source	220/110 V AC(PREDEFINED)
Power consumption	< 35 Watt.
Stand by consumption	< 2 Watt.
Power output	30 Watt(RMS)
Sound output	107 dB @ 1 meter @ 30W.

ENVIRONMENTAL: -

Temperature	0 to +60 C.
Humidity	0 to 95% Rh non-condensing.
Enclosure	Dustproof fully gasketed.

MECHANICAL: -

Body	ABS.
SURFACE FINISH	MATT
Dimensions	200 x 160 x 29 mm.
Net weight kgs	.850 kg.
Standard mounting	Vertical wall.

INDUSTRIAL AUTOMATION SIMPLIFIED.

VOIZLINK.

FF 78 RAJAT ARCADE, MIDC T-POINT,
AMRAWATI ROAD, WADI,
NAGPUR -440023.MAHARASHTRA ,INDIA.

PHONE:-+917104-321913, +917104-224381

Fax:- +917104-224381.

Cell: - +9198226 95746, +919145427003, +919822941190.

Website:- www.voizlink.in.E-mail: - info@voizlink.in.

“(Specifications and description subjected to change without prior notice)”